



Quick Reference Guide for PhoneMail Users


PhoneMail Systems
Release 6.3

How PhoneMail Helps You

The PhoneMail system helps you because it:

- Answers your telephone automatically and plays your personal greeting.
- Accepts and stores voice messages in your PhoneMail mailbox.
- Lets you play back your messages at your convenience.
- Lets you send and receive messages anytime, from anywhere.
- Notifies you of new messages through pagers and telephones.

Your Telephone Keypad



Contents

This quick reference guide tells you:

- How to access PhoneMail, get help, and leave PhoneMail.
- How to use PhoneMail's most popular features.
- How to use PhoneMail's telecommunications device for the deaf (TDD) features.
- How to use the PhoneMail decision tree.
- Where to write your access numbers and personal distribution lists.

February 1998

Revision 1 October 1998

Job No. 4619

PhoneMail is a registered trademark, and PhoneMail SP is a trademark of Siemens Business Communication Systems Inc.

Siemens is a registered trademark of Siemens AG.

Copyright Siemens Business Communication Systems Inc. 1998. All rights reserved.

Accessing Your Mailbox

Direct Access

1. Dial the PhoneMail *direct access number*.
2. Press **#** if calling from your own extension, or
if calling from another extension, dial your *extension number* (or your *name* if permitted), then press **#**.
3. Dial your *password*, then press **#**.

Callback Access (Available in PhoneMail Rel. 6.0 or later)

1. From your extension, press the *callback button* on your ROLMphone telephone (or your telephone's equivalent *repeat dial* or *speed dial* button).
2. Dial your *password*, then press **#**.

The first time you access the PhoneMail system, change your password. (Refer to “Changing PhoneMail Messages” on page 8.)

Your PhoneMail Access Numbers

Your system administrator provides access numbers. Write yours here:

Direct access number _____

Guest access number _____

TDD access number _____

Forwarded or transfer access number _____

Getting Help

Press **0** to get help in using the PhoneMail system.

Leaving PhoneMail

When you finish using the PhoneMail system, you can:

Hang up, or press ***** **7** **6** to *disconnect from* the PhoneMail system.

Listening to Your Messages

1. **Access** your PhoneMail mailbox.
2. Press **3** to *listen*.

While you are listening to messages, use the following control features. Key words are in **bold**.

While you listen to your messages...	Press
Speed <i>Decrease speed</i> of message.	7
<i>Increase speed</i> of message.	9
Volume <i>Decrease volume</i> of messages and prompts.	8
<i>Increase volume</i> of messages and prompts.	5
Headers <i>Skip current header, play message.</i>	3
Skip to <i>previous header</i> .	7 2
Skip to <i>next header</i> .	2
Messages <i>Stop</i> message: * , <i>continue</i> playback: 3 .	* 3
<i>Replay message</i> from beginning.	* 7 3
Replay <i>last few words</i> .	* 7 8
Skip <i>next few words</i> .	* 9 8
Skip to <i>end of message</i> .	* 9 3
Skip to <i>next queue</i> .	* 9 1
<i>Save</i> message.	* 4
<i>Delete</i> message.	* 6
<i>Stop</i> message, skip to <i>next header</i> .	* 2
<i>Stop</i> message, skip to <i>previous header</i> .	* 7 2
<i>Stop</i> message, <i>replay header</i> .	* 7 7
<i>End</i> PhoneMail session.	* 7 6
<i>Stop</i> message, <i>return home</i> .	* 7 #


Recording Messages

1. **Access** your mailbox.
2. Press **1** to **record**.

As you record messages, use the following control features; key words are in **bold**:

While you record your messages...	Press
Skip Instruction	Skip instructions on how to record, so you can begin recording your message. 1
Recording	Record message. 1
	Stop recording (ready for addressing). * #
Addressing	Enter address extensions , each followed by: #
	Enter address names ; dial last name, then first name until recognized, followed by: #
Delivery	Regular delivery. #
	Special delivery. 3
	Cancel delivery. 6
Special Delivery	Mark return receipt requested. 1
	Mark private . 2
	Mark urgent . 3
Stopping and Pausing	Stop * , continue 1 recording. * 1
	Stop recording, start over (re-record message). * 6 1
	Stop recording, cancel delivery of message. * 6 #
Replay	Stop recording, replay what you just recorded. * 7 3
	Stop recording, replay last few words . * 7 8
Quit	End session / disconnect from system. * 7 6

Decision Tree



Recording Messages (continued)

Use these control features when you call someone and PhoneMail answers.

Recording messages when PhoneMail answers <i>your</i> call...	Press
Recording Messages	<i>Wait for the record tone</i> after the greeting, then, <i>record your message</i> , or,
	<i>skip the greeting</i> , and <i>record your message</i> now. 1

Changing PhoneMail Messages

1. **Access** your mailbox, then use the applicable keys below.

To change your name, greetings, prompt level or password...	Press
Personal Greetings	8 1 1
	While recording the greeting, stop and <i>replay</i> it. * 7 3
	While recording the greeting, delete and <i>rerecord</i> it. * 6 1
	When you are <i>finished</i> recording the greeting. * #
Name	8 4 1
	When you are <i>finished</i> recording your name. * #
Prompts	Change to <i>abbreviated</i> prompts. 9 2 2
	Change to <i>regular</i> prompts. 9 2 1
Password	9 3
	Enter the <i>new password</i> followed by: *

Other Options and Features

Transferring Out

To transfer out from home state...		Press
Transferring Out	Transfer out of the PhoneMail system.	7 0
	Transfer to the <i>fax server</i> .	7 4
	Transfer (if you have called someone and the PhoneMail system answers).	0

Using a TDD

To use a TDD:		
Setting up the TDD	Dial the TDD access number.	
	Place the handset in the TDD cradle.	
	Upon connection to the PhoneMail system, press:	#
	If calling from your own extension , press:	#
	If calling from another extension, dial your extension number (or name) followed by:	#
	Dial your password , followed by:	#
Sending a message through TDD	Access your mailbox (as above), followed by:	1
	After GA appears, use your TDD to compose your message , followed by:	* #
	Address the message . (Refer to “Addressing” under “Recording Messages” on page 5.)	

Other Options and Features (continued)

Using the Enhanced Multilingual Feature

The optional enhanced multilingual system permits callers to select one of two languages and TDD.

1. Press **(*)** or **(0)** at any time to invoke the prompt:

“For instruction in <language>, press <number>.”

Using the Voice-Activated Call Routing Feature

The voice-activated call routing feature is an optional speech recognition feature. There are no changes to prompts or the decision tree.

Using the Decision Tree

Examine the decision tree on page 6 to become familiar with the PhoneMail system's option paths. When in doubt, follow the PhoneMail prompts.

We Want Your Comments...

Reader Comment Form

**Siemens PhoneMail Systems
Quick Reference Guide for PhoneMail Users, Release 6.3
G341-1702-01**

Use this form to provide us with your comments, suggestions, or corrections regarding this document.

Fax your comments to the following number:

(408) 492-2306

To leave a message regarding this document using Siemens PhoneMail voice messaging system, call the following number:

Documentation Feedback Line 1-800-445-7656

Date: _____

Your name (optional): _____

Company name: _____

Address: _____

Telephone number: _____ **Fax number:** _____

E-mail address: _____

Section and page number: _____

Comments: _____

Thank you for your comments.

Note: Siemens Business Communications, Inc. publications are not stocked at the location to which this form is addressed. Direct requests for publications, or for assistance in using your Siemens system, contact your Siemens representative or local Siemens branch office.

Note: If mailed in the USA, no postage is necessary. For residents outside the USA, place in an envelope and affix appropriate postage.

Reader Comment Form


Siemens PhoneMail Systems

Fold and Tape


Please Do Not Staple

Fold and Tape

SIEMENS



NO POSTAGE
NECESSARY
IF MAILED
IN THE
UNITED STATES



BUSINESS REPLY MAIL

FIRST CLASS PERMIT No. 1103 SANTA CLARA, CA

POSTAGE WILL BE PAID BY ADDRESSEE

Siemens Business Communications
Product Information Development, MS 321
P.O. Box 58075
Santa Clara, CA, USA 95052-8075



Fold and Tape

Please Do Not Staple

Fold and Tape